



Take the View with You!

QUICK START GUIDE

(VOLK)

voice Activation 🥌

Tab or Say "Focus"

Press or Say "Capture"

• •

ISTA

Back Home

Focus Brigh

volk.com

PREPARATION



Be sure device is fully charged before use. Turn on the device by pressing the small button on the right side of the device.

Note: Default password is 1234.





Before performing any imaging, have an authorized person dilate the patient's eyes to at least 5 mm.



Attach the eye cup to VistaView device.

PREPARATION



app.

Click "Launch VistaView" to open the

Accept Volk Optical Inc. VistaView™ Terms and Conditions after reading carefully. Scroll to the bottom to click I Understand and Agree. Access the Terms and Conditions or the Instructions for Use anytime by selecting Settings > Support



Enter a password for export. 6 Note: Store this password in a safe **location**, as the password can only be changed or reset with the old password.

PREPARATION: OPTIONAL



For best results when using the Voice Activation feature during imaging, train the device to recognize your voice and pronunciation of the words "Focus" and "Capture". Press **Continue**.



To train the device, tap the microphone icon and repeat the word "Focus" and "Capture" five times each. A confirmation screen will appear when the set up is complete.

CLINIC SETTINGS	~
IMAGE SETTING5	
EXPORT SETTINGS	×
TRAIN VOICE COMMANDS	^
TRAIN CAPTURE	
TRAIN FOCUS	
CHECK FOR UPDATES	~
ABOUT	N

If voice capture set up is skipped, the user can train the keyword anytime in Settings > Voice Capture > Train Keyword.





Back Settings	
New Patient	
Existing Patients	
Device Status: Active Clinic: Volk Optical	



Choose to enter a **New Patient** or select **Existing Patients**.

NEW PATIE	NT		
First Name *			
Lucy			
Last Name *			
Smith			
E-mail			
Phone Num!	ber		
Patient ID 1			
98			
Gender:			
Male 🔘	Female	Other	
Date of Birth	100		
July			-

3 If New Patient is chosen, enter new patient data by filling out the patient information. Click Save and Begin Imaging at the end of the form.



If **Existing Patient** is chosen, select an existing patient from the list by clicking **Next** to image that patient.

← බ Back Home Focus Brightness
Voice Activation
Tap or Say "Focus"
Press or Say "Capture"
Lucy Smith Jul 08 1984
∢ () ■





6 To adjust the focus mode, select the • Focus icon then select Focus Assist mode or Manual mode.

← û Back Home	៊ុ ្ឌ Focus Brightness
Press or Say	"Capture"
Lucy Smith Jul 08 1984	

If using manual focus, use the buttons on the right-hand side of the screen to increase or decrease the focus by one diopter increments until the image is clear.

← û Back Home Focus Brightness
Brightness
Voice Activation
Tap or Say "Focus"
Press or Say "Capture"
Lucy Smith Jul 08 1984
< ● ■

To adjust the brightness, select the **Brightness** icon. Start with the lowest brightness and increase as needed.



If using voice capture to image, turn on the Voice Activation feature by activating the toggle button, as shown. Simply say the word "Focus" to obtain the best focus and "Capture" to capture an image once lined up and in focus.





The patient and examiner should be seated facing each other. Use your dominant hand to hold the VistaView and use your non-dominant hand to stabilize the device by positioning the fingers just behind the eye cup as shown.





Ask the patient to look over your shoulder or to fixate at a spot near your ear. Approach the pupil, keeping the device vertical and in a portrait orientation. Stabilize by resting fingers on patient's forehead.



Locate the retina, which can be seen as a small reflection within the pupil. If Focus-Assist is enabled, tap the focus button when you locate the optic disc. Now that the focus is locked for this eye, you can readjust the camera position if needed.



The correct imaging distance is reached when the retina completely fills the imaging window. Note: Do not be afraid to gently push the device closer to the patient - the eye cup is flexible and the device will not touch the patient's eye.





The correct working distance is reached when the entire field of view is filled with the retina without any dark spots and shadows. If you feel the need to readjust focus, tap the focus button one more time for a clear, sharp image.



5 Capture the image by pressing Capture or by saying "Capture" if the Voice Capture feature is turned on.

GENERATING A REPORT



Accept or reject images. If needed, repeat the process from step 9 to step 15 to obtain more images.

16

Back Home Focus Brightness	
Voice Activation	
Tap or Say "Focus"	
Press or Say "Capture"	
Jul 08 1984 Done	
_	

When imaging is complete, press **Done**.



After imaging the patient, review and select the images to include in the report by selecting the circle in the lower right corner of the image to add a green check mark. Click on an image to enlarge.

GENERATING A REPORT



When viewing enlarged images, there is an option to add a red free image to the standard image. Add a red free image by checking the box. Click the back button to return to the image review page.

← û Back Home	Capture
Click to enlarge	Click to enlarge
Click to enlarge	
NOTES	
Healthy eyes, recommen once a year	d following up
Noted By*	
Dr Volk	
	Generate Report
Device Status: Active	Clinic: Volk Optical
◀ ()	•



convey patient history, key findings and recommendations by typing in the space provided. Notes cannot be edited, but more notes can be added to improve traceability. Press Generate Report to create a report.



Once a report is generated, the report is ready to be reviewed and saved. To edit the report images or add notes, press Edit. To finish, press Save & Close. To share the report. press Share and choose how to share the report.

WIRELESS TRANSFER





Select Transfer Patient Files.

Search by Patier	nt Name or ID	
Data Encry	PATIENT FILE	Filte
Name 🗸	Last Imaged	/
Smith Lucy	Feb 22 2021	Transfer
Patel Nirav	Feb 22 2021	Transfer
Lopez Miguel	Feb 22 2021	Transfe
Li Charles	Feb 22 2021	Transfe
Kim Alice	Feb 22 2021	Transfe
Kapoor Drishti	Feb 22 2021	Transfe
James Ron	Feb 22 2021	Transfe
¢	(Transfer All	Patient Da

By default, all patient files will be encypted to protect your data. To transfer patient files the user must decrypt the exported patient data. Tap the lock icon, or the transfer button next to each listed patient, or transfer all patients data button.

WIRELESS TRANSFER



Please enter your VistaView password to decrypt patient data. This will be the same password you assigned in step 6 of the preparation section.



You will now be able to access all patient files arranged in folders. You can select individual patient profiles or select 'View All Patient Data' to access all patient folders.

← û Back Home	< Share
VistaView/	
S_L_1	
J_R_2	
K_A_3	
L_M_4	
L_C_5	
P_D_7	
P_N_6	
Device Status: Active	Clinic:
۹ ۵	

6 Using the check boxes, choose all the folders you want to share and then select the \$\\$Share icon.

WIRELESS TRANSFER

4:20 🖪 🗳 🛕 P 🔹	♥ 🛙 98%
Back Home	Share
L_M_4/	
2021_Jan_27	
🙂 Share with Add	d to Dropbox
	JUST ONCE ALWAYS
Use a different app	
📌 Upload to Pho	tos
A Save to Drive	
◀	

Select the preferred method to share your data.

← û Back Home	< Share
VistaView/P_N_6/2021_Jan_27/	_
040352_OD.dcm	
040352_OD.jpg	
e40352_OD.dng	~
040408_OS.dcm	
040408_05.jpg	
040408_OS.dng	
040350.pdf	
Device Status: Active	Clinic:
4	

You can also select individual images and reports from patients for sharing if you so wish. Select the patient required patient folder, select the images needed and tap the Share **<** icon.

WIRED TRANSFER



To transfer files to a PC, make sure to connect the device via USB-C cable to a PC and make sure that your VistaView application is running. **Before proceeding, you** should decrypt data on your VistaView device.

← û Ø Back Home Settings
Search by Patient Name or ID
WARNING: You are about to disable data encryption in the VisitaView folder will be unencrypted unit on the VisitaView folder will be unencrypted unit you do the total total about the visitavit total data will remain unencrypted unit! you restart total data will remain unencrypted unit! you restart total data will be total total total total be transmitted in an unencrypted data will be unencrypted. Do not leave you dovice unattended total comparison data will be total total total total total total total unencrypted. Do not leave you dovice unattended total comparison data will be total
User password
Confirm
C Transfer All Patient Data
Device Status: Active

Once the device is connected, follow steps #1 and #2 of Wireless transfer section. Read the notification carefully and enter your password.



3 Once the password is entered, the data is temporarily decrypted and available for transfer.

WIRED TRANSFER



devices and drives section of a PC. To access the patient folders, select This PC > VistaView > Internal shared storage.



Once you select the VistaView folder, select the patient to view > the date to view. Copy the files to a desired location.

alt_autocycle

DCIM

VistaView

TROUBLESHOOTING IMAGES



Image is too bright: Correct this by changing the Brightness settings. Decrease the brightness level found on the imaging screen to decrease the image brightness. (Instructions: Imaging step #8 on page 6.)



Image is too dark: Correct this by changing the **Brightness** settings. Increase the brightness level found on the imaging screen to brighten the image brightness. (Instructions: Imaging step #8 on page 6.)



Image is not in focus: If using focus assist mode, wait until the focus is locked and check that the focus is satisfactory before capturing the image. If focus-assist mode does not suffice, switch to manual focus mode. Adjust the diopter value until the image is clear.

(Instructions: Imaging step #6 on page 6.)



Image is blurry: This may be a result of the patient's eye movements. Ask the patient to fixate at a point above your shoulder or at your ear to help keep their gaze steady. Hold the device steady when capturing the image.



Glare on image: If there is a glare at the top of the image, the imaging distance is too far away. Shorten the working distance by moving the device closer to the patient to remove the glare. If there is a glare at the bottom of the image, move further away from the eye.



Macula not centered: Ask the patient to fixate at a point above your shoulder or at your ear to help keep their gaze steady. Adjust the angle of the device such that the face of the device is parallel to the patient. If issue persists, follow calibration steps in the Instructions for Use on page 48.





. ٠ ۲



Take the View with You!

Volk Optical Inc. 7893 Enterprise Drive Mentor, Ohio 44060 USA www.volk.com

ML-1717 Rev C